

Processor settings VXS

| Categories | | SURFACE-MOUNT SPEAKER | | |
|---------------------------|------------|-----------------------|-------------|--------------|
| Model Name | | VXS8 | VXS5 | |
| MTX-MRX library file name | | VXS8.ce3 | VXS5.ce3 | VXS5_sub.ce3 |
| Drive Mode | | Passive | Passive | Passive |
| Output Name | | Full-range | Full-range | Full-range |
| Gain | (dB) | 0.0 | 0.0 | 0.0 |
| Delay | (ms) | none | none | none |
| Polarity | | Normal | Normal | Normal |
| HPF | Freq (Hz) | 45.0 | 60.0 | 97.2 |
| | Slope (dB) | 24 | 24 | 24 |
| | Type | Butterworth | Butterworth | Butterworth |
| LPF | Freq (Hz) | | | |
| | Slope (dB) | | | |
| | Type | | | |
| PEQ1 | Freq (Hz) | 64.9 | 75.0 | 145 |
| | Level (dB) | 3.0 | 7.0 | -3.0 |
| | Type | Bell | Bell | Bell |
| | Q | 3.5 | 2.7 | 3.0 |
| | Bandwidth | 0.411 | 0.531 | 0.479 |
| PEQ2 | Freq (Hz) | 7,100 | 145 | 250 |
| | Level (dB) | -3.0 | -3.0 | 3.0 |
| | Type | Bell | Bell | Bell |
| | Q | 4.2 | 3.0 | 2.2 |
| | Bandwidth | 0.343 | 0.479 | 0.650 |
| PEQ3 | Freq (Hz) | | 250 | 2,240 |
| | Level (dB) | | 3.0 | 1.0 |
| | Type | | Bell | Bell |
| | Q | | 2.2 | 3.2 |
| | Bandwidth | | 0.650 | 0.449 |
| PEQ4 | Freq (Hz) | | 2,240 | 10,600 |
| | Level (dB) | | 1.0 | -1.5 |
| | Type | | Bell | Bell |
| | Q | | 3.2 | 3.8 |
| | Bandwidth | | 0.449 | 0.379 |
| PEQ5 | Freq (Hz) | | 10,600 | |
| | Level (dB) | | -1.5 | |
| | Type | | Bell | |
| | Q | | 3.8 | |
| | Bandwidth | | 0.379 | |
| PEQ6 | Freq (Hz) | | | |
| | Level (dB) | | | |
| | Type | | | |
| | Q | | | |
| | Bandwidth | | | |
| Limiter | Threshold | | | |
| | Attack | | | |
| | Release | | | |

Processor settings VXS-F

| Categories | | COMPACT SURFACE-MOUNT SPEAKER | |
|---------------------------|------------|-------------------------------|---------------|
| Model Name | | VXS3F | |
| MTX-MRX library file name | | VXS3F.ce3 | VXS3F_sub.ce3 |
| Drive Mode | | Passive | Passive |
| Output Name | | Full-range | Full-range |
| Gain | (dB) | 0.0 | 0.0 |
| Delay | (ms) | none | none |
| Polarity | | Normal | Normal |
| HPF | Freq (Hz) | 60.0 | 95.0 |
| | Slope (dB) | 24 | 24 |
| | Type | Butterworth | Butterworth |
| LPF | Freq (Hz) | | |
| | Slope (dB) | | |
| | Type | | |
| PEQ1 | Freq (Hz) | 95.0 | 250 |
| | Level (dB) | 6.0 | -1.5 |
| | Type | Bell | Bell |
| | Q | 3.5 | 4.0 |
| | Bandwidth | 0.411 | 0.360 |
| PEQ2 | Freq (Hz) | 250 | 475 |
| | Level (dB) | -1.5 | 1.5 |
| | Type | Bell | Bell |
| | Q | 4.0 | 6.0 |
| | Bandwidth | 0.360 | 0.240 |
| PEQ3 | Freq (Hz) | 475 | 2,800 |
| | Level (dB) | 1.5 | -1.0 |
| | Type | Bell | Bell |
| | Q | 6.0 | 5.0 |
| | Bandwidth | 0.240 | 0.288 |
| PEQ4 | Freq (Hz) | 2,800 | 9,000 |
| | Level (dB) | -2.0 | -1.0 |
| | Type | Bell | Bell |
| | Q | 5.0 | 4.5 |
| | Bandwidth | 0.288 | 0.320 |
| PEQ5 | Freq (Hz) | 9,000 | |
| | Level (dB) | -2.0 | |
| | Type | Bell | |
| | Q | 4.5 | |
| | Bandwidth | 0.320 | |
| PEQ6 | Freq (Hz) | | |
| | Level (dB) | | |
| | Type | | |
| | Q | | |
| | Bandwidth | | |
| Limiter | Threshold | | |
| | Attack | | |
| | Release | | |

Processor settings VXS-M

| Categories | | MINI SURFACE-MOUNT SPEAKER | |
|---------------------------|------------|----------------------------|------------------|
| Model Name | | VXS1 ML | |
| MTX-MRX library file name | | VXS1ML.ce3 | VXS1ML_sub.ce3 |
| Drive Mode | | Passive | Passive |
| Output Name | | Full-range | Full-range |
| Gain | (dB) | 0.0 | 0.0 |
| Delay | (ms) | none | none |
| Polarity | | Normal | Normal |
| HPF | Freq (Hz) | 100.0 | 160.0 |
| | Slope (dB) | 24 | 24 |
| | Type | Butterworth | Butterworth |
| LPF | Freq (Hz) | | |
| | Slope (dB) | | |
| | Type | | |
| PEQ1 | Freq (Hz) | 345 | 345 |
| | Level (dB) | -1.0 | -1.0 |
| | Type | Bell | Bell |
| | Q | 3.0 | 3.0 |
| | Bandwidth | 0.479 | 0.479 |
| PEQ2 | Freq (Hz) | 800 | 800 |
| | Level (dB) | 2.0 | 2.0 |
| | Type | Bell | Bell |
| | Q | 2.0 | 2.0 |
| | Bandwidth | 0.714 | 0.714 |
| PEQ3 | Freq (Hz) | 4,500 | 4,500 |
| | Level (dB) | -2.0 | -2.0 |
| | Type | Bell | Bell |
| | Q | 1.0 | 1.0 |
| | Bandwidth | 1.388 | 1.388 |
| PEQ4 | Freq (Hz) | 10,000 | 10,000 |
| | Level (dB) | 2.0 | 2.0 |
| | Type | H.SHELF 12dB/Oct | H.SHELF 12dB/Oct |
| | Q | | |
| | Bandwidth | | |
| PEQ5 | Freq (Hz) | | |
| | Level (dB) | | |
| | Type | | |
| | Q | | |
| | Bandwidth | | |
| PEQ6 | Freq (Hz) | | |
| | Level (dB) | | |
| | Type | | |
| | Q | | |
| | Bandwidth | | |
| Limiter | Threshold | | |
| | Attack | | |
| | Release | | |

Processor settings VXS-S

| Categories | | Subwoofer | | |
|---------------------------|------------|-------------|---------------------|-------------|
| Model Name | | VXS10S | VXS10ST | VXS3S |
| MTX-MRX library file name | | VXS10S.ce3 | VXS10ST.ce3 | VXS3S.ce3 |
| Drive Mode | | Passive | Passive (Hi-Z only) | Passive |
| Output Name | | Sub | Sub | Sub |
| Gain | (dB) | 0.0 | 0.0 | 0.0 |
| Delay | (ms) | none | none | none |
| Polarity | | Normal | Normal | Normal |
| HPF | Freq (Hz) | 40.0 | 40.0 | 50.0 |
| | Slope (dB) | 24 | 24 | 24 |
| | Type | Butterworth | Butterworth | Butterworth |
| LPF | Freq (Hz) | 109 | 109 | 218 |
| | Slope (dB) | 48 | 48 | 24 |
| | Type | Butterworth | Butterworth | Butterworth |
| PEQ1 | Freq (Hz) | 63.0 | 63.0 | 75.0 |
| | Level (dB) | 3.0 | 3.0 | 1.5 |
| | Type | Bell | Bell | Bell |
| | Q | 3.5 | 3.5 | 2.5 |
| | Bandwidth | 0.411 | 0.411 | 0.573 |
| PEQ2 | Freq (Hz) | 212 | 212 | 200 |
| | Level (dB) | -6.0 | -6.0 | 1.5 |
| | Type | Bell | Bell | Bell |
| | Q | 8.0 | 8.0 | 2.0 |
| | Bandwidth | 0.180 | 0.180 | 0.714 |
| PEQ3 | Freq (Hz) | | | |
| | Level (dB) | | | |
| | Type | | | |
| | Q | | | |
| | Bandwidth | | | |
| PEQ4 | Freq (Hz) | | | |
| | Level (dB) | | | |
| | Type | | | |
| | Q | | | |
| | Bandwidth | | | |
| PEQ5 | Freq (Hz) | | | |
| | Level (dB) | | | |
| | Type | | | |
| | Q | | | |
| | Bandwidth | | | |
| PEQ6 | Freq (Hz) | | | |
| | Level (dB) | | | |
| | Type | | | |
| | Q | | | |
| | Bandwidth | | | |
| Limiter | Threshold | | | |
| | Attack | | | |
| | Release | | | |